



BULKHEAD



5 year warranty

## FLXE118-Ex-LED

IP 66



**Application:** locations requiring escape route and exit lighting in potentially explosive atmospheres.

**Body:** Aluminium alloy with powder paint finish

**Emergency:** Maintained or Non-maintained, >3hrs autonomy

**Diffuser:** Borosilicate glass tube

**Mounting:** Ceiling/Wall mounting bracket included

**ATEX certified:** Zone 1/21

Ex d IIC T6 Gb  
 Ex tb IIIC T80°C Db IP66 IK08

**AmbT:** -20°C to +50°C

**Voltage:** 220-240V AC/DC (standard), 10VA

**Light source:** 2 x 1.2W LED, 200lm

**Termination:** L1, L2, L3, N: max. 2x2.5mm<sup>2</sup>  
 PE terminal: max. 2x6mm<sup>2</sup>  
 External earth terminal: max. 2x6mm<sup>2</sup>

**Entries:** 2 x M20 (glands not included)

**Battery:** Ni-MH 3.6V, 2.2Ah  
 microprocessor controlled charging, discharging and battery control

**Weight:** 4kg

**Optional:** Pole - Pole mounting bracket

Dali - Dali compatible driver

Voltage - 24V AC/DC, 110-127V AC/DC

Code	Voltage	Pictogram
FLXE118-Ex-LED-0-NONE	24VAC/DC	
FLXE118-Ex-LED-2-NONE	110-127VAC/DC	None
FLXE118-Ex-LED-3-NONE	220-240VAC/DC	
FLXE118-Ex-LED-0-UP	24VAC/DC	
FLXE118-Ex-LED-2-UP	110-127VAC/DC	
FLXE118-Ex-LED-3-UP	220-240VAC/DC	
FLXE118-Ex-LED-0-DOWN	24VAC/DC	
FLXE118-Ex-LED-2-DOWN	110-127VAC/DC	
FLXE118-Ex-LED-3-DOWN	220-240VAC/DC	
FLXE118-Ex-LED-0-LEFT	24VAC/DC	
FLXE118-Ex-LED-2-LEFT	110-127VAC/DC	
FLXE118-Ex-LED-3-LEFT	220-240VAC/DC	
FLXE118-Ex-LED-0-RIGHT	24VAC/DC	
FLXE118-Ex-LED-2-RIGHT	110-127VAC/DC	
FLXE118-Ex-LED-3-RIGHT	220-240VAC/DC	
FLXE118-Ex-LED-0-EXIT	24VAC/DC	
FLXE118-Ex-LED-2-EXIT	110-127VAC/DC	
FLXE118-Ex-LED-3-EXIT	220-240VAC/DC	

Code	Accessories
FLXE118-Em-KIT	Complete exit label kit

Pole Mounting bracket:



Ceiling/Wall Mounting bracket:

